

To: Ameren Electric Service Manual Holder

The latest catalog number information for the Ameren approved meter mounting devices list dated July 2015 is available on the Ameren website: <http://www.ameren.com/servicemanual>

The changes are list as the follow:

- Erickson
 - ❖ Add CT enclosures CT-43, 44 and CT-81, 83
 - ❖ Remove CT enclosure with fused disconnect for 201 to 400 amp services
- Talon/Landis&GYR
 - ❖ Add meter pedestals with clamp jaw lever bypass
 - ❖ Add individual meter sockets with clamp jaw lever bypass for 320 amp and below
 - ❖ Added meter/mains combination units for 200 amp
 - ❖ Added meter/mains cold sequence
 - ❖ Added multi gang units for 200 amp
 - ❖ Added CT and PT enclosures
- Siemens
 - ❖ Add modular meter stacks
 - ❖ Add meter/mains for 320 amp
- Square D
 - ❖ Add RC3040M200SL
 - ❖ Add EZ Meter-Pak Meter Sockets
 - ❖ Remove UTH4330T
 - ❖ Add 1009722-SQD
- Eaton
 - ❖ Add 1009722-CH
 - ❖ Remove1008792-CH

At this site, you will also be able to get the latest Ameren Service Manual as well as register your company to receive immediate notice of any updates.

If you have any questions, please email them to ElectricServiceManual@ameren.com or fax to Service manual 314-206-0233.

SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

MILBANK METER MOUNTING EQUIPMENT LIST

WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	MAX AMPS	INSTALLATION TYPE	BY-PASS	CATALOG NUMBERS LEVER BY PASS	No. Terminal	Max Hub Size (in)	DIMENSIONS-HxWxD (in)
TEMPORARY POWER - METER MAINS											
3	1	100	120/240	-	0-125A	SELF-CONTAINED OH ONLY	N/A	U5101-XL-100MB-11GR	4	2 1/2"	19 1/4 X 9 1/8 X 5 5/5
								U5101-XL-11GR			19 1/4 X 9 1/8 X 5 5/5
3	1	100	120/240	-	0-125A	SELF-CONTAINED UG ONLY	N/A	U4908-O-100MB-11GR	4	2 1/2"	24 15/16 X 9 X 3 5/16
								U4908-O-11GR			24 15/16 X 9 X 3 5/16
3	1	200	120/240	-	0-200A	SELF-CONTAINED OH ONLY	N/A	U5098-XL-200S-10GR	4	2 1/2"	32 X 14 X 5 1/2
METER MAINS WITH TRANSFER SWITCH FOR EMERGENCY POWER											
3	1	125	120/240	-	0-125A	SELF-CONTAINED OH ONLY- METER MAIN COMBO W/ DISCONNECT FOR AUXILIARY GENERATOR APPLICATIONS	LEVER	U5871-XL-100-5T9-AMS W/ K5830 KIT	5	2 1/2"	33 1/2 X 14 1/8 X 4 1/2
3	1	125	120/240	-	0-125A	SELF-CONTAINED OH ONLY- METER MAIN COMBO W/ DISCONNECT FOR AUXILIARY GENERATOR APPLICATIONS	LEVER	U6012-XL-100-K1-5T6-AMS W/ K5830 KIT	5	2 1/2"	39.25 X 14.13 X 4.5
3	1	200	120/240	-	0-200A	SELF-CONTAINED OH ONLY- METER MAIN COMBO W/ DISCONNECT FOR AUXILIARY GENERATOR APPLICATIONS	LEVER	U5871-XL-200-5T9-AMS W/ K5820 OR K5815 KIT	5	2 1/2"	33 1/2 X 14 1/8 X 4 1/2
3	1	200	120/240	-	0-200A	SELF-CONTAINED OH/UG- METER MAIN COMBO W/ DISCONNECT FOR AUXILIARY GENERATOR APPLICATIONS	LEVER	U6012-XL-200-K1-5T6-AMS W/ K5815 KIT OR K5820	5	2 1/2"	39.25 X 14.13 X 4.5
3	1	200	120/240	-	0-200A	SELF-CONTAINED OH ONLY- METER MAIN COMBO W/ DISCONNECT FOR AUXILIARY GENERATOR APPLICATIONS	LEVER	U4834-XL-200-5T9-AMS W/ AUXILIARY BREAKER ORDERED SEPARATELY- UQFP SERIES BREAKER	5	2 1/2"	39X17X5 1/2
INDIVIDUAL METER SOCKETS											
3	1	125	120/240	-	0-125A	SELF-CONTAINED OH ONLY	LEVER	U6193-YL-QG-AMS	5	1 1/4"	18.5 X 10 X 4.844
								U6193-RL-QG-AMS		2 1/2"	18.5 X 10 X 4.844
3	1	200	120/240	-	0-200A	SELF-CONTAINED OH/UG	LEVER	U9551-RXL-QG-AMS	5	4"	19 X 13 X 4.844
3	1	200	120/240	-	0-200A	SELF-CONTAINED OH ONLY	LEVER	U9550-RRL-QG-AMS	5	4"	18.5 X 10 X 4.844
								U9550-RDL-QG-AMS		2"	18.5 X 10 X 4.844
METER MAINS COMBO											
3	1	125	120/240	-	0-125A	SELF -CONTANIED OH ONLY -METER MAIN COMBO WITH DISCONNECT	LEVER	U3791N-RXL-100-5T9-AMS	5	4"	34 X 13 X 4.844
							LEVER	U5871-XL-100-5T9-AMS	5	2 1/2"	33 1/2 X 14 1/8 X 4 1/2
							LEVER	U6012-XL-100-K1-5T6-AMS	5	2 1/2"	39.25 X 14.13 X 4.5



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

MILBANK METER MOUNTING EQUIPMENT LIST

WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	MAX AMPS	INSTALLATION TYPE	BY-PASS	CATALOG NUMBERS LEVER BY PASS	No. Terminal	Max Hub Size (in)	DIMENSIONS-HxWxD (in)		
3	1	200	120/240	-	0-200A	SELF-CONTAINED OH/UG WITH DISC.	LEVER	U6012-XL-200-K1-5T6-AMS	5	2 1/2"	39.25 X 14.13 X 4.5		
						SELF-CONTAINED OH WITH DISC.	LEVER	U3791N-RXL-200-5T9-AMS	5	4"	34 X 13 X 4.844		
3	1	200	120/240	-	0-200A	SELF-CONTAINED OH WITH DISC.	LEVER	U5871-XL-200-5T9-AMS	5	2 1/2"	33 1/2 X 14 1/8 X 4 1/2		
4	3	200	120/208 120/240	-	0-200A	SELF-CONTAINED OH/UG	LEVER	U5750-RXL-200-BL-AMS	7	4"	34 X 17 3/8 X 5 3/4"		
3	1	400	120/240	-	201-400A	SELF-CONTAINED OH/UG W/ 2-200A DISC	LEVER	U5059-X-2/200-K3L5T6-AMS	5	4"	42x15x4 7/8		
						SELF-CONTAINED OH/UG W/ 2-200A DISC		U5890-X-2/200-K3L-5T6-AMS			35x24.5x6		
						SELF-CONTAINED OH/UG W/ 2-200A DISC		U5891-X-2/200-K3L-5T6-MLK-AMS			35x29.5x6		
						SELF-CONTAINED OH/UG W/ 2-200A DISC		U5892-X-2/200-K3L-5T6-MLK-AMS			35x29.5x6		
INDIVIDUAL METER SOCKETS													
3	1	400	120/240	-	201-400A	SELF-CONTAINED OH/UG	LEVER	U5786-X-2/K2-5T6-BL-AMS U5786-X-K3-K2-5T6-BL-AMS	5	4"	38 3/4 x 17 3/4 x 6 1/2 38 3/4 x 17 3/4 x 6 1/2		
						SELF-CONTAINED OH/UG		U4778-X-BL W/ K3865 KIT			38 3/4 x 17 3/4 x 6 1/2		
						SELF-CONTAINED OH/UG		U5740-X-K3L-K2L-5T6-AMS			31.69 X 15 X 4.85		
						SELF-CONTAINED OH ONLY		U1079-X-QG-K3-K2-5T6-AMS			38 3/4 X 13 X 4 7/8		
						SELF-CONTAINED OH ONLY		U4363-X-QG-K3-K2-5T6-AMS			28 1/4x13x4 27/32		
INDIVIDUAL METER SOCKETS													
3	1	200	120/240	-	0-200A	SELF-CONTAINED OH/UG	LEVER	U9551-RXL-QG-AMS	5	4"	19 X 13 X 4 7/8		
						SELF-CONTAINED OH		U9550-RDL-QG-AMS			2"	18 1/2 X 10 X 4 7/8	
						SELF-CONTAINED OH/UG		U9581-RXL-QG-AMS			5	4"	19 x 13 x 4 7/8
						SELF-CONTAINED OH/UG		UAP9551-XL-QG-HSP			5	2 1/2"	19 x 13 x 4 25/32
						SELF-CONTAINED OH/UG		UAP9581-XL-QG			5	2 1/2"	19 x 13 x 4 25/32
3	NETWORK	200	120/208	-	0-200A	SELF-CONTAINED OH/UG	LEVER	U9551-RXL-QG-AMS	5	4"	19 X 13 X 4 7/8		
						SELF-CONTAINED OH		U9550-RDL-QG-AMS			5	2"	18 1/2 X 10 X 4 7/8
						SELF-CONTAINED OH/UG		UAP9581-XL-QG			5	2 1/2"	19 x 13 x 4 25/32
						SELF-CONTAINED OH/UG		U9581-RXL-QG-AMS			5	4"	19 x 13 x 4 25/32
						SELF-CONTAINED OH/UG		UAP9551-XL-QG-HSP			5	2 1/2"	19 x 13 x 4 25/32
3	3 DELTA	200	240	-	0-200A	SELF-CONTAINED OH/UG	LEVER	U9551-RXL-QG-AMS	5	4"	19 X 13 X 4 7/8		
						SELF-CONTAINED OH		U9550-RDL-QG-AMS			5	2"	18 1/2 X 10 X 4 7/8
						SELF-CONTAINED OH/UG		U9581-RXL-QG-AMS			5	4"	19 x 13 x 4 25/32
						SELF-CONTAINED OH/UG		UAP9551-XL-QG-HSP			5	2 1/2"	19 x 13 x 4 25/32
						SELF-CONTAINED OH/UG		UAP9581-XL-QG			5	2 1/2"	19 x 13 x 4 25/32



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

MILBANK METER MOUNTING EQUIPMENT LIST

WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	MAX AMPS	INSTALLATION TYPE	BY-PASS	CATALOG NUMBERS LEVER BY PASS	No. Terminal	Max Hub Size (in)	DIMENSIONS-HxWxD (in)
4	3	200	120/240 120/208	-	0-200A	SELF-CONTAINED OH/UG	LEVER	U9701-RXL-QG-AMS	7	4"	19 X 13 X 4 7/8
						SELF-CONTAINED OH		U9700-RRL-QG-AMS	7	4"	18 1/2 X 10 X 4 7/8
3	3 DELTA	400	240	-	201-400	SELF-CONTAINED OH ONLY	LEVER	U1079-X-QG-K3-K2-5T6-AMS	5	4"	38 3/4 X 13 X 4 7/8
3	3 DELTA	400	240	-	201-400	SELF-CONTAINED OH/UG	LEVER	U5740-X-K3L-K2L-5T6-AMS W/ K5979	5	4"	31.69 X 15 X 4.85
4	3	400	120/240	-	201-400A	SELF-CONTAINED OH/UG	LEVER	U4911-X-QG-BL-AMS	7	4"	38 3/4x17 3/4x6 1/2
4	3Y	400	120/208	-	201-400A	SELF-CONTAINED OH/UG	LEVER	U4911-X-QG-BL-AMS	7	4"	38 3/4x17 3/4x6 1/2
MULTI POSITION - RESIDENTIAL											
3	1	200A/ Position	120/240	2 GANG HORIZONTAL	0-200A	SELF-CONTAINED OH/UG	LEVER	U2872-XT-QG-AMS	5	2 1/2"	25 1/4 X 32 1/8 X 6
3	1	200A/ Position	120/240	3 GANG HORIZONTAL	0-200A	SELF-CONTAINED OH/UG	LEVER	U2873-XT-QG-AMS	5	2 1/2"	25 1/4 X 42 3/16 X 6
3	1	200A/ Position	120/240	4 GANG HORIZONTAL	0-200A	SELF-CONTAINED OH/UG	LEVER	U2874-XT-QG-AMS	5	2 1/2"	25 1/4 X 52 1/4 X 6
3	1	200A/ Position	120/240	5 GANG HORIZONTAL	0-200A	SELF-CONTAINED OH/UG	LEVER	U2875-XT	5	2 1/2"	25 1/4 X 62 5/16 X 6
3	1	200A/ Position	120/240	6 GANG HORIZONTAL	0-200A	SELF-CONTAINED OH/UG	LEVER	U2876-XT	5	2 1/2"	31 1/4 X 72 3/8 X 6
3	1	200A/ Position	120/240	2 GANG HORIZONTAL AND VERTICAL	0-200A	SELF-CONTAINED OH/UG W/ DISC.	LEVER	U4372-XT-5T9-AMS U5972-XT-5T9	5	2 1/2"	VERT-48 x 27 3/4 x 6 HORIZ-34 X 36 3/8 X 5 31/32
3	1	200A/ Position	120/240	3 GANG HORIZONTAL AND VERTICAL	0-200A	SELF-CONTAINED OH/UG W/ DISC.	LEVER	U4373-XT-5T9-AMS U5973-XT-5T9	5	2 1/2"	VERT-60 x 27 3/4 x 6 HORIZ-34 x 46 1/2 x 5 31/32
3	1	200A/ Position	120/240	4 GANG HORIZONTAL AND VERTICAL	0-200A	SELF-CONTAINED OH/UG W/ DISC.	LEVER	U4374-XT-5T9-AMS U5974-XT-5T9	5	2 1/2"	VERT-48 x 45 x 6 HORIZ-34 X 57 1/16 X 5 31/32
3	1	200A/ Position	120/240	5 GANG HORIZONTAL AND VERTICAL	0-200A	SELF-CONTAINED OH/UG W/ DISC.	LEVER	U4375-XT-5T9-AMS U5975-XT-5T9	5	2 1/2"	VERT-60 x 45 x 6 HORIZ-34 X 67 1/8 X 5 31/32
3	1	200A/ Position	120/240	6 GANG HORIZONTAL AND VERTICAL	0-200A	SELF-CONTAINED OH/UG W/ DISC.	LEVER	U4376-XT-5T9-AMS U5976-XT-5T9	5	2 1/2"	VERT-60 x 45 x 6 HORIZ-34 X 77 9/16 X 5 31/32
4	3	200A/ Position	240V MAX.	2 GANG HORIZONTAL	0-200A	SELF-CONTAINED OH/UG	LEVER	U2732-XT	7	2 1/2"	25 1/4 X 32 1/8 X 6
4	3	200A/ Position	240V MAX.	3 GANG HORIZONTAL	0-200A	SELF-CONTAINED OH/UG	LEVER	U2733-XT	7	2 1/2"	25 1/4 X 42 3/16 X 6
4	3	200A/ Position	240V MAX.	4 GANG HORIZONTAL	0-200A	SELF-CONTAINED OH/UG	LEVER	U2734-XT	7	2 1/2"	25 1/4 X 52 1/4 X 6
4	3	200A/ Position	240V MAX.	5 GANG HORIZONTAL	0-200A	SELF-CONTAINED OH/UG	LEVER	U2735-XT	7	2 1/2"	25 1/4 X 62 5/16 X 6
4	3	200A/ Position	240V MAX.	6 GANG HORIZONTAL	0-200A	SELF-CONTAINED OH/UG	LEVER	U2736-XT	7	2 1/2"	31 1/4 X 72 3/8 X 6

SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

MILBANK METER MOUNTING EQUIPMENT LIST

WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	MAX AMPS	INSTALLATION TYPE	BY-PASS	CATALOG NUMBERS LEVER BY PASS	No. Terminal	Max Hub Size (in)	DIMENSIONS-HxWxD (in)
WALL MOUNTED METER PEDESTAL (Also available Stand-Alone for additional burial kit)											
3	1	200	120/240	-	0-200A	Self-contained	LEVER	U9108-0-CECHA	5		62"x9"x4 1/8"
3	1	320	120/240	-	400A	Self-contained	LEVER	U1748-0-5T9-WI	5		64" x 13" x 4 27/32"
MOBILE HOME TYPE PEDESTALS											
3	1	100A/200A	120/240	MOBILE HOME SINGLE POSITION DIRECT BURIAL	0-200A	SELF-CONTAINED UNDERGROUND ONLY	LEVER	U5701-0-100S-5T6-AMS & K5415 U5701-0-200S-5T6-AMS & K5415	5	N/A	80 X 9.88 X 4.13
3	1	100A/200A	120/241	MOBILE HOME SINGLE POSITION PAD MOUNT		SELF-CONTAINED UNDERGROUND ONLY	LEVER	U5703-0-100S-5T9 U5703-0-200S-5T9	5	N/A	80 X 9.88 X 4.13
3	1	100A/200A	120/240	MOBILE HOME 2 GANG POSITION DIRECT BURIAL	0-200A	SELF-CONTAINED UNDERGROUND ONLY	LEVER	U5702-0-100S-5T6-AMS & K5415 U5702-0-200S-5T6-AMS & K5415	5	N/A	80 X 9.88 X 4.13
PEDESTALS - COMMERCIAL											
3	1	200A	120/240	-	0-200A	SELF-CONTAINED UNDERGROUND ONLY	LEVER	CP3B51C1PAAOMO1	5	N/A	48 X 16 X 17
3	1	200A	120/240	-	0-200A	SELF-CONTAINED UNDERGROUND ONLY	LEVER	CP3B51C1PBAOMO2	5	N/A	48 X 24 X 17
3	1	200A	120/240	-	0-200A	SELF-CONTAINED UNDERGROUND ONLY	LEVER	CP3B51C1PBAOMO3	5	N/A	48 X 24 X 17
3	1	200A	480	-	0-200A	SELF-CONTAINED UNDERGROUND ONLY - (REPLACED BY NEXT MODEL W/ CS1 SUFFIX)	LEVER	CP3B51D1PBAOMO1	5	N/A	48 x 24 x 17
3	1	200A	480	-	0-200A	SELF-CONTAINED UNDERGROUND ONLY - COLD SEQUENCE (FUSED DISC.)	LEVER	CP3B51D1PBAOMO1CS1	5	N/A	48 x 24 x 17
3	1	200A	120/240	-	0-200A	SELF-CONTAINED UNDERGROUND ONLY	LEVER	CP3B62C2NBAOMO1	5	N/A	48 x 24 x 17
3	1	200A	120/240	-	0-200A	SELF-CONTAINED UNDERGROUND ONLY	LEVER	CP3B51110A22SL1 - K3865	5	N/A	48 x 16 x 17
3	1	200A	120/240	-	0-200A	SELF-CONTAINED UNDERGROUND ONLY	LEVER	CP3B52110A22SL1 - K3865	5	N/A	48x16x17
3	1	200A	120/240	-	0-200A	SELF-CONTAINED UNDERGROUND ONLY	LEVER	CP3B51115A22 - K3865	5	N/A	48 x 16 x 17
3	1	200A	120/240	-	0-200A	SELF-CONTAINED UNDERGROUND ONLY	LEVER	CP3B52119A22 - K3865	5	N/A	48 x 16 x 17



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

MILBANK METER MOUNTING EQUIPMENT LIST

WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	MAX AMPS	INSTALLATION TYPE	BY-PASS	CATALOG NUMBERS LEVER BY PASS	No. Terminal	Max Hub Size (in)	DIMENSIONS-HxWxD (in)
480V COLD SEQUENCE SOCKET AND DISC. COMBINATION OR 480V METER SOCKET (480V BREAKER OR FUSED DISC. WITH IN 4' OF SOCKET)											
3	1	200	480	COLD SEQUENCE	0-200A		LEVER	U5764-X-200-5T-CB-AMS	5	4"	43x13x4.84
								U5784-O-200-5T-CB-AMS			28x26x4.84
								U5784-O-200-5T-TF			26x26x4.84
								U5764-X-200-5T-TF			43x13x4.84
3	1	200	480	480V M-S ONLY	0-200A		LEVER	U9551-RXL-QG-AMS	5	4"	19x13x4 25/32
								U9581-RXL-QG-AMS			19x13x4 25/32
3	3 DELTA	200	480	COLD SEQUENCE	0-200A		LEVER	U5765-X-200-CB-AMS	5	4"	43x13x4.84
								U5785-O-200-CB-AMS			28x26x4.84
								U5785-O-200-TF			28x26x4.84
								U5765-X-200-TF			43x13x4.84
3	3 DELTA	200	480	480V M-S ONLY	0-200A		LEVER	U9551-RXL-QG-AMS	5	4"	19x13x4 25/32
								U9581-RXL-QG-AMS			19x13x4 25/32
4	3Y	200	277/480	COLD SEQUENCE	0-200A		LEVER	U5767-X-200-CB-AMS	7	4"	43x13x4.84
								U5787-O-200-CB-AMS			28x26x4.84
								U5787-O-200-TF			28x26x4.84
								U5767-X-200-TF			43x13x4.84
4	3Y	200	277/480	480V M-S ONLY	0-200A		LEVER	U9701-RXL-QG-AMS (NEUTRAL ISOLATION KIT REQUIRED-K1047)	7	4"	19x13x4 7/8
BUSSED CT CABINETS - (Note: Single Door Cabinets: 24" and below & Double Door Cabinet: above 24")									PT CABINET #		
3	1	800A MAXIMUM	120/240	-	401-800A	BUSSED CT CABINET-BAR TYPE CT'S	N/A	CT244811HC & K4797 INSERT	NOT REQUIRED	N/A	24 X 48 X 11
								CT304811HCAMS W/ K5931 OR K4797			30 X 48 X 11
								CT364811HCAMS W/ K5931 OR K4797			36 X 48 X 11
3	3 DELTA	800A MAXIMUM	240	-	401-800A	BUSSED CT CABINET-BAR TYPE CT'S	N/A	CT244811HC W/ K4797 INSERT	NOT REQUIRED	N/A	24 X 48 X 11
								CT304811HCAMS W/ K5931 OR K4797			30 X 48 X 11
								CT364811HCAMS W/ K5931 OR K4797			36 X 48 X 11
3	3 DELTA	800A MAXIMUM	480	-	201-800A	BUSSED CT CABINET-BAR TYPE CT'S	N/A	CT244811HC W/ K4797 INSERT	PT48 (AL or AR)	N/A	24 X 48 X 11
								CT304811HCAMS W/ K5931 OR K4797			30 X 48 X 11
								CT364811HCAMS W/ K5931 OR K4797			36 X 48 X 11
4	3	800A MAXIMUM	120/240	-	401-800A	BUSSED CT CABINET-BAR TYPE CT'S	N/A	CT304811HCAMS W/ K5930 OR K4798	NOT REQUIRED	N/A	30 X 48 X 11
								CT364811HCAS W/ K5930 OR K4798			36 X 48 X 11



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

MILBANK METER MOUNTING EQUIPMENT LIST

WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	MAX AMPS	INSTALLATION TYPE	BY-PASS	CATALOG NUMBERS LEVER BY PASS	No. Terminal	Max Hub Size (in)	DIMENSIONS-HxWxD (in)
4	3Y	800A MAXIMUM	120/208	-	401-800A	BUSSECT CABINET-BAR TYPE CT'S	N/A	CT304811HCAMS W/ K5930 OR K4798	NOT REQUIRED	N/A	30 X 48 X 11
								CT364811HCAMS W/ K5930 OR K4798			36 X 48 X 11
4	3Y	800A MAXIMUM	277/480	-	201-800A	BUSSECT CABINET-BAR TYPE CT'S	N/A	CT304811HCAMS W/ K5930 OR K4798	PT48 (AL or AR)	N/A	30 X 48 X 11
								CT364811HCAMS W/ K5930 OR K4798			27.5 X 8 X 8.63
							Notes:	1. PT-48 L or R - Older Model will be replaced with PT-48AL or AR after inventory is depleted.			27.5 X 8 X 8.63
								2. PT-48AL OR AR - New Model			36 X 12 X 8

ILLINOIS CT Rated Pre-Wired Meter Sockets (Customer Supplied)

3	1	ALL CT RATED APPLICATIONS	120/240	-	401A-and LARGER	CT Metering 8 Terminal Application (Customer Supplied)	LEVER	U4496-XL-WC-41-AMS	8	1 1/2	22x12x4.84
3	1	ALL CT RATED APPLICATIONS	480	-	201A AND LARGER	CT Metering 8 Terminal Application (Customer Supplied)	LEVER	U4496-XL-WC-41-AMS	8	1 1/2	22x12x4.84
3	3 DELTA	ALL CT RATED APPLICATIONS	240	-	401A-and LARGER	CT Metering 8 Terminal Application (Customer Supplied)	LEVER	U4496-XL-WC-41-AMS	8	1 1/2	22x12x4.84
3	3 DELTA	ALL CT RATED APPLICATIONS	480	-	201A AND LARGER	CT Metering 8 Terminal Application (Customer Supplied)	LEVER	U4496-XL-WC-41-AMS	8	1 1/2	22x12x4.84
4	3	ALL CT RATED APPLICATIONS	120/240	-	401A-and LARGER	CT Metering 13 Terminal Application (Customer Supplied)	LEVER	U4497-XL-WC-61-AMS	13	1 1/2	22x12x4.84
4	3Y	ALL CT RATED APPLICATIONS	120/208	-	401A-and LARGER	CT Metering 13 Terminal Application (Customer Supplied)	LEVER	U4497-XL-WC-61-AMS	13	1 1/2	22x12x4.84
4	3Y	ALL CT RATED APPLICATIONS	277/480	-	201A AND LARGER	CT Metering 13 Terminal Application (Customer Supplied)	LEVER	U4497-XL-WC-61-AMS	13	1 1/2	22x12x4.84



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

ERICKSON CT & PT ENCLOSURES

WIRES	PHASE	VOLTS	MAX AMPS	INSTALLATION TYPE	CATALOG NUMBER	Terminals
BUSSED CT CABINETS - WALL MOUNTED						
3	3	240	201-400A	400A CT METERING -BAR TYPE CT'S BUSSED CABINET	CT-43-AMR	N/A
3	3	120/240	201-400A	400A CT METERING -BAR TYPE CT'S BUSSED CABINET	CT-44-AMR	N/A
4	3	120/208	201-400A	400A CT METERING -BAR TYPE CT'S BUSSED CABINET	CT-44-AMR	N/A
3	3 DELTA	480	201-400A	400A CT METERING -BAR TYPE CT'S BUSSED CABINET	CT-43-PTL-AMR	N/A
4	3	277/480	201-400A	400A CT METERING -BAR TYPE CT'S BUSSED CABINET	CT-44-PTL-AMR	N/A
3	1	120/240	401-800A	800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-81-AMR	N/A
3	3	240	401-800A	800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-83-AMR	N/A
4	3	120/240	4011-800A	800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-84-AMR	N/A
4	3Y	120/208	401-800A	600A/800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-84-AMR	N/A
3	3 DELTA	480	401-800	800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-83-PTL-AMR	N/A
4	3Y	277/480	401-800A	800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-84-PTL-AMR	N/A
3	3	240	801-1200A	1200A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-123-AMR	N/A
4	3	120/240	801-1200A	1200A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-124-AMR	N/A
4	3Y	120/208	801-1200A	1200A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-124-AMR	N/A
3	3 DELTA	480	801-1200A	1200A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-123-PTL-AMR	N/A
4	3Y	277/480	801-1200A	1200A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-124-PTL-AMR	N/A
3	3	240	1201-1600A	1600 CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-163-AMR	N/A
4	3	120/240	1201-1600A	1600 CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-164-AMR	N/A
4	3Y	120/208	1201-1600A	1600 CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-164-AMR	N/A
3	3 DELTA	480	1201-1600A	1600 CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-163-PTL-AMR	N/A
4	3Y	277/480	1201-1600A	1600 CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-164-PTL-AMR	N/A
3	3	240	1601-2000A	2000 CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-203-AMR	N/A
4	3	120/240	1601-2000A	2000 CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-204-AMR	N/A
4	3Y	120/208	1601-2000A	2000 CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-204-AMR	N/A
3	3 DELTA	480	1601-2000A	2000 CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-203-PTL-AMR	N/A
4	3Y	277/480	1601-2000A	2000 CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-204-PTL-AMR	N/A
3	3	240	2001-2500	2500A CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-253-AMR	N/A
4	3	120/240	2001-2500	2500A CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-254-AMR	N/A
3	3 DELTA	480	2001-2500	2500A CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-253-PTL-AMR	N/A



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

ERICKSON CT & PT ENCLOSURES

WIRES	PHASE	VOLTS	MAX AMPS	INSTALLATION TYPE	CATALOG NUMBER	Terminals
4	3Y	277/480	2001-2500	2500A CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-254-PTL-AMR	N/A
3	3	240	2501-3000A	3000A CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-303-AMR	N/A
4	3	120/240	2501-3000A	3000A CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-304-AMR	N/A
4	3Y	120/208	2501-3000A	3000A CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-304-AMR	N/A
3	3 DELTA	480	2501-3000A	3000A CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-303-PTL-AMR	N/A
4	3Y	277/480	2501-3000A	3000A CT METERING WINDOW TYPE CT'S BUSSED CABINET	CT-304-PTL-AMR	N/A
400-800A CT & PT SECTIONS (BOTTOM) WITH DISCONNECTS (TOP), WALL MOUNTED LINE ENTRY AT BOTTOM, LOAD EXIT AT TOP						
3	3 DELTA	480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH CIRCUIT BREAKER DISCONNECT	CTBKD-365-PT-AMR	N/A
3	3 DELTA	480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTBP-365-PT-AMR	N/A
3	3 DELTA	480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTBP-3644-PT-AMR	N/A
3	3 DELTA	480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS365-PT-AMR	N/A
4	3Y	277/480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH CIRCUIT BREAKER DISCONNECT	CTBKD-465N-PT-AMR	N/A
4	3Y	277/480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTBP-465N-PT-AMR	N/A
4	3Y	277/480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTBP4644N-PT-AMR	N/A
4	3Y	277/480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS465N-PT-AMR	N/A
3	1	120/240	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS326N-AMR	N/A
3	3 DELTA	240	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS326-AMR	N/A
3	3 DELTA	480	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS366-PT-AMR	N/A
4	3	120/240	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS426N-AMR	N/A
4	3Y	120/208	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS426N-AMR	N/A
4	3Y	277/480	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS466N-PT-AMR	N/A
3	1	120/240	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS327N-AMR	N/A
3	3 DELTA	240	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS327-AMR	N/A
3	3 DELTA	480	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS367-PT-AMR	N/A

SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

ERICKSON CT & PT ENCLOSURES

WIRES	PHASE	VOLTS	MAX AMPS	INSTALLATION TYPE	CATALOG NUMBER	Terminals
4	3	120/240	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS427N-AMR	N/A
4	3Y	120/208	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS427N-AMR	N/A
4	3Y	277/480	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	BFCTMS467N-PT-AMR	N/A
400-800A CT & PT SECTIONS (TOP) WITH DISCONNECTS (BOTTOM), WALL MOUNTED LINE ENTRY AT TOP, LOAD EXIT AT BOTTOM (See Notes)						
3	3 DELTA	480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH CIRCUIT BREAKER DISCONNECT	CTAKD-365-PT-AMR	N/A
3	3 DELTA	480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTAP-365-PT-AMR	N/A
3	3 DELTA	480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTAP-3644-PT-AMR	N/A
3	3 DELTA	480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS365-PT-AMR	N/A
4	3Y	277/480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH CIRCUIT BREAKER DISCONNECT	CTAKD-465N-PT-AMR	N/A
4	3Y	277/480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTAP-465N-PT-AMR	N/A
4	3Y	277/480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTAP4644N-PT-AMR	N/A
4	3Y	277/480	201-400A	400A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS465N-PT-AMR	N/A
3	1	120/240	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS326N-AMR	N/A
3	3 DELTA	240	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS326-AMR	N/A
3	3 DELTA	480	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS366-PT-AMR	N/A
4	3	120/240	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS426N-AMR	N/A
4	3Y	120/208	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS426N-AMR	N/A
4	3Y	277/480	401-600A	600A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS466N-PT-AMR	N/A

SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

ERICKSON CT & PT ENCLOSURES

WIRES	PHASE	VOLTS	MAX AMPS	INSTALLATION TYPE	CATALOG NUMBER	Terminals
3	1	120/240	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS327N-AMR	N/A
3	3 DELTA	240	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS327-AMR	N/A
3	3 DELTA	480	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS367-PT-AMR	N/A
4	3	120/240	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS427N-AMR	N/A
4	3Y	120/208	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS427N-AMR	N/A
4	3Y	277/480	601-800A	800A CT METERING BAR TYPE BUSSED CT WITH FUSED DISCONNECT SWITCH	CTMS467N-PT-AMR	N/A

NOTE: CATALOG NUMBERS SERIES "CTMS" MAY BE USED WITH AN OPTIONAL SIDE WIRING GUTTER FOR USE WITH UNDERGROUND SERVICE CONDUCTORS

MULTI MAINS - HOT-SEQUENCE WALL MOUNTED (See Notes)

3	1	120/240	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)4-1	5
3	1	120/240	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)4-2	5
3	1	120/240	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)4-3	5
3	1	120/240	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)4-4	5
3	1	120/208	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)4-1	5
3	1	120/208	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)4-2	5
3	1	120/208	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)4-3	5
3	1	120/208	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)4-4	5
4	3	120/208	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)7-1	7
4	3	120/208	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)7-2	7
4	3	120/208	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)7-3	7
4	3	120/208	0-200A	SELF-CONTAINED OH/UG HOT SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	CM(7/8/9)7-4	7

- Notes:
- 1) CM = Commercial Metering, Hot Sequence, Lever Bypass
 - 2) (7, 8, 9) Main Bus Rating 7 = 800A, 8 = 1200A, 9 = 1600A
 - 3) 4 = 4 Jaw Socket, 7 = 7 Jaw Socket
 - 4) Last # Indicates Number of Meter Positions



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

ERICKSON CT & PT ENCLOSURES

WIRES	PHASE	VOLTS	MAX AMPS	INSTALLATION TYPE	CATALOG NUMBER	Terminals
3	1	120/240	401-600A	600A CT METERING - BAR TYPE CT'S - 600A CT CABINET AND 600A MAIN SWITCH COMBINATION	AMRCTAT326NCM(7/8/9)	SWITCH
					AMRCTALD326NCM(7/8/9)	BREAKER
3	1	120/240	601-800A	800A CT METERING - BAR TYPE CT'S - 800A CT CABINET AND 800A MAIN SWITCH COMBINATION	AMRCTAT327NCM(7/8/9)	SWITCH
					AMRCTAMD327NCM(7/8/9)	BREAKER
4	3	120/208	201-400A	400A CT METERING - BAR TYPE CT'S - 400A CT CABINET AND 400A MAIN SWITCH COMBINATION	AMRCTAT425NCM(7/8/9)	SWITCH
					AMRCTAP425NCM(7/8/9)	SWITCH
4	3	120/208	401-600A	600A CT METERING - BAR TYPE CT'S - 600A CT CABINET AND 600A MAIN SWITCH COMBINATION	AMRCTAT426NCM(7/8/9)	SWITCH
					AMRCTALD426NCM(7/8/9)	BREAKER
4	3	120/208	601-800A	800A CT METERING - BAR TYPE CT'S - 800A CT CABINET AND 800A MAIN SWITCH COMBINATION	AMRCTAT427NCM(7/8/9)	SWITCH
					AMRCTAMD427NCM(7/8/9)	BREAKER

C/T SECTION AT BOTTOM, DISCONNECT AT TOP (HOT SEQUENCE)

3	1	120/240	401-600A	600A CT METERING - BAR TYPE CT'S - 600A CT CABINET AND 600A MAIN SWITCH COMBINATION	AMRCTBLD326NCM(7/8/9)	BREAKER
3	1	120/240	601-800A	800A CT METERING - BAR TYPE CT'S - 800A CT CABINET AND 800A MAIN SWITCH COMBINATION	AMRCTBMD327NCM(7/8/9)	BREAKER
4	3	120/208	401-600A	600A CT METERING - BAR TYPE CT'S - 600A CT CABINET AND 600A MAIN SWITCH COMBINATION	AMRCTBLD426NCM(7/8/9)	BREAKER
4	3	120/208	601-800A	800A CT METERING - BAR TYPE CT'S - 800A CT CABINET AND 800A MAIN SWITCH COMBINATION	AMRCTBMD427NCM(7/8/9)	BREAKER

* (7/8/9) 7 = 800A MAIN BUS, 8 = 1200A MAIN BUS, 9 = 1600A MAIN BUS

MULTI MAINS - COLD SEQUENCE - 480 VOLT (See Notes)

3	1	277/480	0-200A	SELF-CONTAINED OH/UG COLD SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	6CSCM(7/8/9)5-2	5
3	1	277/480	0-200A	SELF-CONTAINED OH/UG COLD SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	6CSCM(7/8/9)5-3	5
4	3	277/480	0-200A	SELF-CONTAINED OH/UG COLD SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	6CSCM(7/8/9)7-1	7
4	3	277/480	0-200A	SELF-CONTAINED OH/UG COLD SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	6CSCM(7/8/9)7-2	7
4	3	277/480	0-200A	SELF-CONTAINED OH/UG COLD SEQUENCE MODULAR METERING W/ BRKR OR CLASS "T" FUSE PULL OUT	6CSCM(7/8/9)7-3	7

Note:

- 1) 6 CSCM = Cold Sequence Commercial Metering (480V)
- 2) (7, 8, 9) Main Bus Rating 7 = 800A, 8 = 1200A, 9 = 1600A
- 3) 5 = 5 Jaw Socket, 7 = 7 Jaw Socket
- 4) Last # Indicates Number of Meter Positions.



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

ERICKSON CT & PT ENCLOSURES

WIRES	PHASE	VOLTS	MAX AMPS	INSTALLATION TYPE	CATALOG NUMBER	Terminals
C/T & P/T SECTION AT TOP, DISCONNECT AT BOTTOM (HOT SEQUENCE)						
4	3Y	277/480	201-400A	400A CT METERING - BAR TYPE CT'S - 400A CT CABINET W/ PT PROVI. AND 400A MAIN SWITCH COMBINATION	AMRCTAT465N6CM(7/8/9) AMRCTAKD465N6CM(7/8/9) AMRCTAP465N6CM(7/8/9)	SWITCH BREAKER SWITCH
4	3Y	277/480	401-600A	600A CT METERING - BAR TYPE CT'S - 600A CT CABINET W/ PT PROVI. AND 600A MAIN SWITCH COMBINATION	AMRCTAT466N6CM(7/8/9) AMRCTALD466N6CM(7/8/9)	SWITCH BREAKER
4	3Y	277/480	601-800A	800A CT METERING - BAR TYPE CT'S - 800A CT CABINET W/ PT PROVI. AND 800A MAIN SWITCH COMBINATION	AMRCTAT467N6CM(7/8/9) AMRCTAMD467N6CM(7/8/9)	SWITCH BREAKER
4	3Y	277/480	401-600A	600A CT METERING - BAR TYPE CT'S - 600A CT CABINET W/ PT PROVI. AND 600A MAIN SWITCH COMBINATION	AMRCTBLD466N6CM(7/8/9)	BREAKER
4	3Y	277/480	601-800A	800A CT METERING - BAR TYPE CT'S - 800A CT CABINET W/ PT PROVI. AND 800A MAIN SWITCH COMBINATION	AMRCTBMD467N6CM(7/8/9)	BREAKER
* (7/8/9) 7 = 800A MAIN BUS, 8 = 1200A MAIN BUS, 9 = 1600A MAIN BUS						
CT & PT ENCLOSURES - PAD MOUNTED, FREE STANDING						
3	1	120/240	321-800A	600A/800A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-81-AMR	N/A
3	3 DELTA	240	321-800A	600A/800A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-83-AMR	N/A
3	3 DELTA	480	201-400A	400A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-43-PTL-AMR	N/A
3	3 DELTA	480	401-800A	600A/800A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-83-PTL-AMR	N/A
4	3	120/240	321-800A	600A/800A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-84-AMR	N/A
4	3Y	120/208	321-800A	600A/800A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-84-AMR	N/A
4	3Y	277/480	201-400A	400A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-44-PTL-AMR	N/A
4	3Y	277/480	401-800A	600A/800A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-84-PTL-AMR	N/A
3	3	240	801-1200A	1200A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-123-AMR	N/A
4	3	120/240	801-1200A	1200A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-124-AMR	N/A
4	3Y	120/208	801-1200A	1200A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-124-AMR	N/A
3	3 DELTA	480	801-1200A	1200A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-123-PTL-AMR	N/A
4	3Y	277/480	801-1200A	1200A CT METERING - BAR TYPE CT'S BUSSED CT CABINET	PMCT-124-PTL-AMR	N/A
3	3	240	1201-1600A	1600A CT METERING - WINDOW TYPE CT'S BUSSED CT CABINET	PMCT-163-AMR	N/A
4	3	120/240	1201-1600A	1600A CT METERING - WINDOW TYPE CT'S BUSSED CT CABINET	PMCT-164-AMR	N/A
4	3Y	120/208	1201-1600A	1600A CT METERING - WINDOW TYPE CT'S BUSSED CT CABINET	PMCT-164-AMR	N/A
3	3 DELTA	480	1201-1600A	1600A CT METERING - WINDOW TYPE CT'S BUSSED CT CABINET	PMCT-163-PTL-AMR	N/A
4	3Y	277/480	1201-1600A	1600A CT METERING - WINDOW TYPE CT'S BUSSED CT CABINET	PMCT-164-PTL-AMR	N/A



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

ERICKSON CT & PT ENCLOSURES

WIRES	PHASE	VOLTS	MAX AMPS	INSTALLATION TYPE	CATALOG NUMBER	Terminals
3	3	240	1601-2000A	2000A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-203-AMR	N/A
4	3	120/240	1601-2000A	2000A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-204-AMR	N/A
4	3Y	120/208	1601-2000A	2000A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-204-AMR	N/A
3	3 DELTA	480	1601-2000A	2000A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-203-PTL-AMR	N/A
4	3Y	277/480	1601-2000A	2000A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-204-PTL-AMR	N/A
3	3	240	2001-2500A	2500A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-253-AMR	N/A
4	3	120/240	2001-2500A	2500A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-254-AMR	N/A
4	3Y	120/208	2001-2500A	2500A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-254-AMR	N/A
3	3 DELTA	480	2001-2500A	2500A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-253-PTL-AMR	N/A
4	3Y	277/480	2001-2500A	2500A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-254-PTL-AMR	N/A
3	3	240	2501-3000A	3000A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-303-AMR	N/A
4	3	120/240	2501-3000A	3000A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-304-AMR	N/A
4	3Y	120/208	2501-3000A	3000A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-304-AMR	N/A
3	3 DELTA	480	2501-3000A	3000A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-303-PTL-AMR	N/A
4	3Y	277/480	2501-3000A	3000A CT METERING - WINDOW TYPE CT'S BUSSEDED CT CABINET	PMCT-304-PTL-AMR	N/A
CT & PT ENCLOSURES, PAD MOUNTED WITH MAIN SWITCH						
3	1	120/240	321-600A	600A CT METERING BAR TYPE BUSSEDED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-326N-AMR	N/A
3	1	120/240	601-800A	800A CT METERING BAR TYPE BUSSEDED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-327N-AMR	N/A
3	3 DELTA	240	321-600A	600A CT METERING BAR TYPE BUSSEDED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-326-AMR	N/A
3	3 DELTA	240	601-800A	800A CT METERING BAR TYPE BUSSEDED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-327-AMR	N/A
3	3 DELTA	480	201-400A	400A CT METERING BAR TYPE BUSSEDED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-365-PT-AMR	N/A
3	3 DELTA	480	401-600A	600A CT METERING BAR TYPE BUSSEDED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-366-PT-AMR	N/A
3	3 DELTA	480	601-800A	800A CT METERING BAR TYPE BUSSEDED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-367-PT-AMR	N/A

SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

ERICKSON CT & PT ENCLOSURES

WIRES	PHASE	VOLTS	MAX AMPS	INSTALLATION TYPE	CATALOG NUMBER	Terminals
4	3	120/240	321-600A	600A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-426N-AMR	N/A
4	3	120/240	601-800A	800A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-427N-AMR	N/A
4	3Y	120/208	321-600A	600A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-426N-AMR	N/A
4	3Y	120/208	601-800A	800A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-427N-AMR	N/A
4	3Y	277/480	201-400A	400A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-465N-PT-AMR	N/A
4	3Y	277/480	401-600A	600A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-466N-PT-AMR	N/A
4	3Y	277/480	601-800A	800A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-467N-PT-AMR	N/A
3	3	240	801-1200A	1200A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-328-AMR	N/A
4	3	120/240	801-1200A	1200A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-428N-AMR	N/A
4	3Y	120/208	801-1200A	1200A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-428N-AMR	N/A
3	3 DELTA	480	801-1200A	1200A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-368-PT-AMR	N/A
4	3Y	277/480	801-1200A	1200A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-468NG6-PT-AMR	N/A
3	3	240	1201-1600A	1600A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-329-AMR	N/A
4	3	120/240	1201-1600A	1600A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-429N-AMR	N/A
4	3Y	120/208	1201-1600A	1600A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-429N-AMR	N/A
3	3 DELTA	480	1201-1600A	1600A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-369-PT-AMR	N/A
4	3Y	277/480	1201-1600A	1600A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-469NG6-PT-AMR	N/A
3	3	240	1601-2000A	2000A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-3210-AMR	N/A
4	3	120/240	1601-2000A	2000A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-4210N-AMR	N/A

SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

ERICKSON CT & PT ENCLOSURES

WIRES	PHASE	VOLTS	MAX AMPS	INSTALLATION TYPE	CATALOG NUMBER	Terminals
4	3Y	120/208	1601-2000A	2000A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-4210N-AMR	N/A
3	3 DELTA	480	1601-2000A	2000A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-3610-PT-AMR	N/A
4	3Y	277/480	1601-2000A	2000A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-4610NG6-PT-AMR	N/A
3	3	240	2001-2500A	2500A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-3211-AMR	N/A
4	3	120/240	2001-2500A	2500A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-4211N-AMR	N/A
4	3Y	120/208	2001-2500A	2500A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-4211N-AMR	N/A
3	3 DELTA	480	2001-2500A	2500A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-3611-PT-AMR	N/A
4	3Y	277/480	2001-2500A	2500A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-4611NG6-PT-AMR	N/A
3	3	240	2501-3000A	3000A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-3212-AMR	N/A
4	3	120/240	2501-3000A	3000A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-4212N-AMR	N/A
4	3Y	120/208	2501-3000A	3000A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-4212N-AMR	N/A
3	3 DELTA	480	2501-3000A	3000A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-3612-PT-AMR	N/A
4	3Y	277/480	2501-3000A	3000A CT METERING BAR TYPE BUSSED CT PAD MOUNTED CABINET WITH DISCONNECT	PMCTMS-4612NG6-PT-AMR	N/A
1200-2000A CT & PT ENCLOSURES AND SERVICE SWITCH, WALL MOUNTED - TOP OR BOTTOM FEED						
3	3 DELTA	240	801-1200A	1200A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT123-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
3	3 DELTA	480	801-1200A	1200A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT123-PT-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
4	3	120/240	801-1200A	1200A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT124-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
4	3Y	120/208	801-1200A	1200A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT124-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
4	3Y	277/480	801-1200A	1200A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT124-PT-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
3	3 DELTA	240	1201-1600A	1600A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT163-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
3	3 DELTA	480	1201-1600A	1600A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT163-PT-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
4	3	120/240	1201-1600A	1600A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT164-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
4	3Y	120/208	1201-1600A	1600A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT164-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

ERICKSON CT & PT ENCLOSURES

WIRES	PHASE	VOLTS	MAX AMPS	INSTALLATION TYPE	CATALOG NUMBER	Terminals
4	3Y	277/480	1201-1600A	1600A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT164-PT-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
3	3 DELTA	240	1601-2000A	2000A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT203-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
3	3 DELTA	480	1601-2000A	2000A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT203-PT-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
4	3	120/240	1601-2000A	2000A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT204-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
4	3Y	120/208	1601-2000A	2000A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT204-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
4	3Y	277/480	1601-2000A	2000A CT METERING BAR TYPE BUSSED CT AND SERVICE SWITCH	CT204-PT-AMR-LE WITH SERIES VL OR VLB SWITCH	N/A
* REFER TO SERIES CTSS-035XX.XX DRAWINGS FOR EQUIPMENT LAYOUT AND SWITCH CATALOG NUMBER						
400A AUXILARY MANUAL FUSED TRANSFER SWITCH AND CT CABINET COMBINATION						
3	3	240	400A	Manual Transfer Switch/ 320A 5T SOCKET	EGT325-5	N/A
4	3	240	400A	Manual Transfer Switch/ 320A 7T SOCKET	EGT425-5N	N/A
3	3	480	400A	Manual Transfer Switch/ 400A CT/PT CABINET	AMRCTPT/EGT365-5	N/A
4	3	277/480	400A	Manual Transfer Switch/ 400A CT/PT CABINET	AMRCTPT/EGT465-5N	N/A
600A AUXILARY MANUAL FUSED TRANSFER SWITCH AND CT CABINET COMBINATION						
3	3	240	600A	Manual Transfer Switch/ 600A CT CABINET	AMRCT/EGT366-6	N/A
4	3	240	600A	Manual Transfer Switch/ 600A CT CABINET	AMRCT/EGT466-6N	N/A
3	3	480	600A	Manual Transfer Switch/ 600A CT/PT CABINET	AMRCTPT/EGT366-6	N/A
4	3	277/480	600A	Manual Transfer Switch/ 600A CT/PT CABINET	AMRCTPT/EGT466-6N	N/A

SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

AMERICAN MIDWEST POWER (AMP) PRODUCTS

Wires	Phase	Max Volts	Max Amps	Installation Type	Catalog #
CURRENT TRANSFORMER "CT" ENCLOSURES					
3	1	600	400	400A Bussed Bar Type Wall Mtd CT Cabinet	AMECTS4-3L
3	1	600	400 to 600	400-600A Bussed Bar Type Wall Mtd CT Cabinet	OH
3	1	600	800	800A Bussed Bar Type Wall Mtd CT Cabinet	AMECT8-3L
4	3	600	400	400A Bussed Bar Type Wall Mtd CT Cabinet	AMECTS4-4L
4	3	600	400 to 600	400-600A Bussed Bar Type Wall Mtd CT Cabinet	AMECT46-4L
4	3	600	800	800A Bussed Bar Type Wall Mtd CT Cabinet	AMECT8-4L
4	3	600	1200	1200A Bussed Bar Type Wall Mtd CT Cabinet (48" Length)	AMECT12-4L (48")
4	3	600	1200	1200A Bussed Bar Type Wall Mtd CT Cabinet (60" Length)	AMECT112-4L (60")
4	3	600	1600	1600A Bussed Window Type Wall Mtd CT Cabinet	AMECT16-4L
4	3	600	2000	2000A Bussed Window Type Wall Mtd CT Cabinet	AMEFCT20-4L
4	3	600	2500	2500A Bussed Window Type Wall Mtd CT Cabinet	AMEFCT25-4L
4	3	600	3000	3000A Bussed Window Type Wall Mtd CT Cabinet	AMEFCT30-4L
4	3	600	800	800A Bussed Bar Type Pad Mtd CT Cabinet	AMESCC8-4ACT
4	3	600	1000	1000A Bussed Bar Type Pad Mtd CT Cabinet	AMESCC10-4ACT
4	3	600	1200	1200A Bussed Bar Type Pad Mtd CT Cabinet	AMESCC12-4ACT
4	3	600	1600	1600A Bussed Window Type Pad Mtd CT Cabinet	AMESCC16-4ACT
4	3	600	2000	2000A Bussed Window Type Pad Mtd CT Cabinet	AMESCC20-4ACT
4	3	600	2500	2500A Bussed Window Type Pad Mtd CT Cabinet	AMESCC25-4ACT
4	3	600	3000	3000A Bussed Window Type Pad Mtd CT Cabinet	AMESCC30-4ACT
COMBINATION "CT" CABINET & MAIN DISCONNECT					
3	1	600	400	400A Bussed Bar type CT Cabinet w/ 400A Main Switch	AMEMCT265J
3	1	600	800	600A Bussed Bar type CT Cabinet w/ 600A Main Switch	AMEMCT266J
3	1	600	800	800A Bussed Bar type CT Cabinet w/ 800A Main Switch	AMEMCT267J
4	3	600	400	400A Bussed Bar type CT Cabinet w/ 400A Main Switch	AMEMCT365J
4	3	600	600	600A Bussed Bar type CT Cabinet w/ 600A Main Switch	AMEMCT266J
4	3	600	800	800A Bussed Bar type CT Cabinet w/ 800A Main Switch	AMEMCT367L
4	3	600	1200	1200A Bussed Bar type CT Cabinet w/ 1200A Main Switch	AMEMCT368L
COMBINATION "CT" CABINET & SIX DISCONNECT					
3	1	600	400-800	400 to 800A Bussed Bar Type CT Cabinet & 6 Disc Panel	AMESCT8-3
4	3	600	400-800	400 to 800A Bussed Bar Type CT Cabinet & 6 Disc Panel	AMESCT8-4
4	3	600	1200	1200A Bussed Bar Type CT Cabinet & 6 Disc Panel	SELF-CONTAINED UG (3" K/O on Left)
TERMINATION BOX					
3	1	600	800	800A Step Bus Pad Mtd Termination Cabinet	AMESCC8-3A
4	3	600	800	800A Step Bus Pad Mtd Termination Cabinet	AMESCC8-4A
4	3	600	1000	1000A Step Bus Pad Mtd Termination Cabinet	AMESCC10-4A
4	3	600	1200	1200A Step Bus Pad Mtd Termination Cabinet	AMESCC12-4A
4	3	600	1600	1600A Step Bus Pad Mtd Termination Cabinet	AMESCC16-4A
4	3	600	2000	2000A Step Bus Pad Mtd Termination Cabinet	AMESCC20-4A
4	3	600	2500	2500A Step Bus Pad Mtd Termination Cabinet	AMESCC25-4A
4	3	600	3000	3000A Step Bus Pad Mtd Termination Cabinet	AMESCC30-4A
PT CABINET					
NA	3	600	NA	PT Enclosure Galvanized	PTB30
NA	3	600	NA	PT Enclosure Painted Transformer Green	PTB30GRN
NA	3	600	NA	PT Enclosure Painted ASA61 Gray	PTB30GRY
METER STACKS - RESIDENTIAL (INDOOR)					
3	1	250	1200A	1 to 12 1PH Sockets Indoor Encl Max 125A CB	RM Style
4	3	250	1200A	1 to 12 1PH Sockets Indoor Encl Max 125A CB	RM Style
METER STACKS - RESIDENTIAL (OUTDOOR)					
3	1	250	1200A	1 to 10 1PH Sockets N3R Encl Max 125A CB	RMR90 Style
4	3	250	1200A	1 to 10 1PH Sockets N3R Encl Max 125A CB	RMR90 Style
3	1	250	1200A	1 to 8 1PH Sockets N3R Encl Max 200A CB	RMR90-2 Style
4	3	250	1200A	1 to 8 1PH Sockets N3R Encl Max 200A CB	RMR90-2 Style
SWITCHBOARD					
3	1	250	800	Indoor or Outdoor Swbd w/Sockets & CT Compartments	FMU Style
4	3	600	3000	Indoor or Outdoor Swbd w/Sockets & CT Compartments	FMU Style



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

TALON/LANDIS&GYR METER SOCKETS LIST

Wires	Phase	Terminals	Volts	Max. Cont.	Installation	Bypass	Catalog #	Closure Plate bnm,	DIMENSIONS		
									Height(in)	Width(in)	Depth(in)
Individual Meter Sockets - Temporary Power											
3	1	4 or 5*	120/240	100	OH	Horn	LGP77RTS	C.P. / 2.5"			
3	1	4 or 5*	120/240	100	UG	Horn	LGP77RBS	N/A			
Meter Pedestal											
3	1	4 or 5*	120/240	200	UG	Lever	MP0606L1200RJL	N/A	96	12	9
3	1	4 or 5*	120/240	200	UG	Lever	MP0406B1200JL2	N/A	96	12	20
3	1	4 or 5*	120/240	200	UG	Lever	MPS0406B1200JL	N/A	96	13.38	9
3	1	4 or 5*	120/240	125	UG	Lever	MPS0406B1125JL	N/A	96	13.38	9
3	1	4 or 5*	120/240	150	UG	Lever	MPS0406B1150JL	N/A	96	13.38	9
3	1	4 or 5*	120/240	100	UG	Lever	MPS0406B1100JL	N/A	96	13.38	9
3	1	4 or 5*	120/240	200	UG	Lever	MPS0406B1200L2	N/A	96	13.38	20
Individual Meter Sockets											
3	1	5	120/240	320	OH/UG	Lever	49905-026	Up to 4" KO	36	20.25	6 1/5
3	1	5	120/240	320	OH/UG	Lever	48104-82WI	L.C.P. / 4"	31	16	5
3	1	5	120/240	125	OH	Lever	42305-02MR	C.P. / 2.5"	18.5	10	4.8
3	1	5	120/240	125	OH	Lever	42395-02MR	C.P. / 2.5"	18.5	10	4.8
3	1	5	120/240	200	OH	Lever	40804-01QG	H.O. / 2.5"	17.5	10	5.2
3	1	5	120/240	200	OH/UG	Lever	40404-02QG	C.P. / 2.5"	19	13	5.2
3	1	5	120/240	200	OH	Lever	41005-01F	H.O. / 2.5"	17.5	10	5.2
3	1	5	120/240	200	OH	Lever	40005-01QG	H.O. / 2.5"	17.5	10	5.2
3	1	5	120/240	200	OH/UG	Lever	40405-02QG	C.P. / 2.5"	19	13	5.2
3	1	5	120/240	200	OH/UG	Lever	9804-8592	C.P. / 2.5"	19	13	5.2
3	1	5	120/240	200	OH/UG	Lever	44305-02MR	C.P. / 4"	19	13	4.9
3	1	5	120/240	200	OH/UG	Lever	42705-02MR	C.P. / 4"	19	13	4.9
3	1	5	120/240	200	OH/UG	Lever	41405-02MR	C.P. / 2.5"	19	13	4.9
3	1	5	120/240	200	OH/UG	Lever	40405-02MR	C.P. / 4"	19	13	4.9
3	1	5	120/240	200	OH	Lever	42405-01MR	C.P. / 4"	18.5	10	4.9
3	1	5	120/240	200	OH	Lever	42425-02MR	C.P. / 4"	18.5	10	4.9
3	1	5	120/240	320/400	OH/UG	Lever	42805-42MR	C.P. / 4"	38.75	17.75	6.5
3	1	5	120/240	320/400	OH/UG	Lever	43005-42MR	C.P. / 4"	38.75	17.75	6.5
3	1	5	120/240	320/400	OH	Lever	47605-82MR	C.P. / 4"	31.7	15	4.9
4	3	7	120/208	200	OH	Lever	42407-01MR	C.P. / 4"	18.5	10	4.9
4	3	7	120/208	200	OH/UG	Lever	44307-02MR	C.P. / 4"	19	13	4.9
4	3	7	120/208	200	OH	Lever	40007-01QG	N.P. / 2.5"	17.5	10	5.2
4	3	7	120/208	200	OH/UG	Lever	40407-02QG	C.P. / 2.5"	19	13	5.2
4	3	7	120/208	320/400	OH/UG	Lever	9804-9109	L.C.P. / 4"	34	20.25	6
4	3	7	120/208	320/400	OH/UG	Lever	49007-01FL	L.C.P. / 4"	34	20.25	6
4	3	7	120/208	320/400	OH/UG	Lever	49807-026	L.C.P. / 4"	34	20.25	6
4	3	7	120/208	320/400	OH/UG	Lever	43005-82MR	L.C.P. / 4"	31.7	15	4.9
4	3	7	120/208	320/400	OH/UG	Lever	42807-02MR	L.C.P. / 4"	38.8	17.8	6.5



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

TALON/LANDIS&GYR METER SOCKETS LIST

Wires	Phase	Terminals	Volts	Max. Cont.	Installation	Bypass	Catalog #	Closure Plate bnm,	DIMENSIONS			
Combination Meter / Mains (Side by Side)												
3	1	5	120/240	320	OH/UG	Lever	LG0816B1400RLTM	L.C.P. / 4"	29"	27	6	
3	1	5	120/240	320	OH/UG	Lever	LMMM0404L1400RLM	L.C.P. / 4"	29	27	6	
3	1	5	120/240	200	OH/UG	Lever	LG0202L1200JL6	L.C.P. / 4"	36.2	16	5	
3	1	5	120/240	200	OH/UG	Lever	LG0202B1200JL6	L.C.P. / 4"	36.2	16	5	
3	1	5	120/240	200	OH/UG	Lever	LG0202L 1200JLC	L.C.P. / 4"	36.2	16	5	
3	1	5	120/240	200	OH/UG	Lever	LG0202B1200JLC	L.C.P. / 4"	36.2	16	5	
4	3	7	120/208	200	OH/UG	Lever	LG0303B3200JLC	L.C.P. / 4"	36.2	16	5	
Combination Meter / Mains - COLD SEQUENCE												
4	3	7	120/208	200	UG	Lever	LG0303CS3200RD	L.C.P. / 4"	28	26	6	Main Brkr. Disconnect (Over/Under)
4	3	7	120/208	200	OH	Lever	LG0303CS3200R	L.C.P. / 4"	43	13	6	Main Brkr. Disconnect (Side by side)
Multi Gang 200 Amp												
3	1	5	120/240	200	OH/UG	Lever	404052-223NU	2 Gang Horizontal				
3	1	5	120/240	200	OH/UG	Lever	404053-223NU	3 Gang Horizontal				
3	1	5	120/240	200	OH/UG	Lever	404054-223NU	4 Gang Horizontal				
3	1	5	120/240	200	OH/UG	Lever	404055-223NU	5 Gang Horizontal				
3	1	5	120/240	200	OH/UG	Lever	404056-223NU	6 Gang Horizontal				
Multi Gang 200 Amp												
4	3	7	120/208	200	OH/UG	Lever	404072-023NU	2 Gang Horizontal				
4	3	7	120/208	200	OH/UG	Lever	404073-023NU	3 Gang Horizontal				
							404074-023NU					
4	3	7	120/208	200	OH/UG	Lever		4 Gang Horizontal				
4	3	7	120/208	200	OH/UG	Lever	404075-223NU	5 Gang Horizontal				
4	3	7	120/208	200	OH/UG	Lever	404076-223NU	6 Gang Horizontal				
Multi Gang 200 Amp												
3	1	5	120/240	200	OH/UG	Lever	404052-223MR	2 Gang Horizontal				
3	1	5	120/240	200	OH/UG	Lever	404053-223MR	3 Gang Horizontal				
3	1	5	120/240	200	OH/UG	Lever	404054-223MR	4 Gang Horizontal				
3	1	5	120/240	200	OH/UG	Lever	404055-223MR	5 Gang Horizontal				
3	1	5	120/240	200	OH/UG	Lever	404056-223MR	6 Gang Horizontal				
Multi Gang 200 Amp												
4	3	7	120/208	200	OH/UG	Lever	404072-223MR	2 Gang Horizontal				
4	3	7	120/208	200	OH/UG	Lever	404073-223MR	3 Gang Horizontal				
4	3	7	120/208	200	OH/UG	Lever	404074-223MR	4 Gang Horizontal				
4	3	7	120/208	200	OH/UG	Lever	404075-223MR	5 Gang Horizontal				
4	3	7	120/208	200	OH/UG	Lever	404076-223MR	6 Gang Horizontal				



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

TALON/LANDIS&GYR METER SOCKETS LIST

Wires	Phase	Terminals	Volts	Max. Cont.	Installation	Bypass	Catalog #	Closure Plate bnm,	DIMENSIONS
-------	-------	-----------	-------	------------	--------------	--------	-----------	--------------------	------------

BUSSED CT CABINETS-WALL MOUNTED

Wires	Phase	Volts	Max. Cont.	Service Type	Catalog #
3	1	120/240	201-400A	400A CT METERING -BAR TYPE CT'S BUSSED CABINET	CT-41-AMR
3	3	240	201-400A	400A CT METERING -BAR TYPE CT'S BUSSED CABINET	CT-43-AMR
3	3	120/240	201-400A	400A CT METERING -BAR TYPE CT'S BUSSED CABINET	CT-44-AMR
4	3	120/208	201-400A	400A CT METERING -BAR TYPE CT'S BUSSED CABINET	CT-44-AMR
3	3 DELTA	480	201-400A	400A CT METERING -BAR TYPE CT'S BUSSED CABINET	CT-43-PTL-AMR
4	3	277/480	201-400A	400A CT METERING -BAR TYPE CT'S BUSSED CABINET	CT-44-PTL-AMR
3	1	120/240	401-800A	800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-81-AMR
3	3	240	401-800A	800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-83-AMR
4	3	120/240	4011-800A	800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-84-AMR
4	3Y	120/208	401-800A	800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-84-AMR
3	3 DELTA	480	401-800	800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-83-PTL-AMR
4	3Y	277/480	401-800A	800A CT METERING BAR TYPE CT'S BUSSED CABINET	CT-84-PTL-AMR



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

SIEMENS METERING DEVICES LIST

Wires	Phase	Terminals	Volts	Service Type	Max. Cont.	Installation	Bypass	Catalog #	MAX HUB	Max. # Cdr's	LENGTH	WIDTH	DEPTH
Meter Mains													
3	1	5	120/240	Residential	320	OH/UG	Lever	MM0404L1400RLM	4.0"	Line: One #4 - 600kcmil	29.00	27.00	6.00
3	1	5	120/240	Main Brkr. Disconnect (Side by Side)	320	OH/UG	Lever	MC0816B1400RLTM	L.C.P. / 4"	Line: One #4 - 600kcmil	29.00	27.00	6.00
Modular Meterstacks													
3	1	5	120/240	1 Gang	225	OH/UG	Lever	WML11225RJ	Bussed	Line: Bussed	27.75	19.50	9.00
3	1	5	120/240	2 Gang	225	OH/UG	Lever	WML21225RJ	Bussed	Line: Bussed	40.75	19.50	9.00
3	1	5	120/240	3 Gang	225	OH/UG	Lever	WML31225RJ	Bussed	Line: Bussed	49.75	19.50	9.00
3	1	5	120/240	4 Gang	225	OH/UG	Lever	WML41225RJ	Bussed	Line: Bussed	62.75	19.50	9.00
3	1	5	120/240	1 Gang	320	OH/UG	Lever	WML11400RJ	Bussed	Line: Bussed	44.00	16.31	9.69
3	1	5	120/240	2 Gang	320	OH/UG	Lever	WML21400RJ	Bussed	Line: Bussed	70.38	23.00	9.69
3	1	5	120/240	1 Gang	225	OH/UG	Lever	WML12225RJ	Bussed	Line: Bussed	27.75	19.50	9.00
3	1	5	120/240	2 Gang	225	OH/UG	Lever	WML22AB225RJ	Bussed	Line: Bussed	40.75	19.50	9.00
3	1	5	120/240	2 Gang	225	OH/UG	Lever	WML22BC225RJ	Bussed	Line: Bussed	40.75	19.50	9.00
3	1	5	120/240	2 Gang	225	OH/UG	Lever	WML22CA225RJ	Bussed	Line: Bussed	40.75	19.50	9.00
3	1	5	120/240	3 Gang	225	OH/UG	Lever	WML32225RJ	Bussed	Line: Bussed	49.75	19.50	9.00
3	1	5	120/240	4 Gang	225	OH/UG	Lever	WML42AB225RJ	Bussed	Line: Bussed	62.75	19.50	9.00
3	1	5	120/240	4 Gang	225	OH/UG	Lever	WML42AB225RJ	Bussed	Line: Bussed	62.75	19.50	9.00
3	1	5	120/240	4 Gang	225	OH/UG	Lever	WML42CA225RJ	Bussed	Line: Bussed	62.75	19.50	9.00
3	1	5	120/240	1 Gang	320	OH/UG	Lever	WML12400RJ	Bussed	Line: Bussed	44.00	16.31	9.69
3	1	5	120/240	2 Gang	320	OH/UG	Lever	WML22400RJ	Bussed	Line: Bussed	70.38	23.00	9.69
4	3	7	208Y/120V	1 Gang	100	OH/UG	Lever	WML13100RJ	Bussed	Line: Bussed	27.75	23.50	9.00
4	3	7	208Y/120V	2 Gang	100	OH/UG	Lever	WML23100RJ	Bussed	Line: Bussed	40.75	23.50	9.00
4	3	7	208Y/120V	3 Gang	100	OH/UG	Lever	WML33100RJ	Bussed	Line: Bussed	49.75	23.50	9.00
4	3	7	208Y/120V	4 Gang	100	OH/UG	Lever	WML43100RJ	Bussed	Line: Bussed	62.75	23.50	9.00
4	3	7	240V	1 Gang	225	OH/UG	Lever	WML13225RJ	Bussed	Line: Bussed	27.75	23.50	9.00
4	3	7	240V	2 Gang	225	OH/UG	Lever	WML23225RJ	Bussed	Line: Bussed	40.75	23.50	9.00



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

SIEMENS METERING DEVICES LIST

Wires	Phase	Terminals	Volts	Service Type	Max. Cont.	Installation	Bypass	Catalog #	MAX HUB	Max. # Cdr's	LENGTH	WIDTH	DEPTH
4	3	7	240V	3 Gang	225	OH/UG	Lever	WML33225RJ	Bussed	Line: Bussed	49.75	23.50	9.00
4	3	7	240V	4 Gang	225	OH/UG	Lever	WML43225RJ	Bussed	Line: Bussed	62.75	23.50	9.00
4	3	7	240V	1 Gang	320	OH/UG	Lever	WML13400RJ	Bussed	Line: Bussed	44.00	16.31	9.69
4	3	7	240V	2 Gang	320	OH/UG	Lever	WML23400RJ	Bussed	Line: Bussed	70.38	23.00	9.69
3	1	5	208Y/120	2 Gang	125	OH/UG	Lever	ML22125RJ	Bussed	Line: Bussed	36.00	14.50	11.50
3	1	5	208Y/120	3 Gang	125	OH/UG	Lever	ML32125RJ	Bussed	Line: Bussed	46.00	14.50	11.50
3	1	5	208Y/120	4 Gang	125	OH/UG	Lever	ML42125RJ	Bussed	Line: Bussed	56.00	14.50	11.50
3	1	5	208Y/120	5 Gang	125	OH/UG	Lever	ML52125RJ	Bussed	Line: Bussed	66.00	14.50	11.50
3	1	5	208Y/120	6 Gang	125	OH/UG	Lever	ML62125RJ	Bussed	Line: Bussed	76.00	14.50	11.50
3	1	5	208Y/120	2 Gang	125	OH/UG	Lever	WML22125RJ	Bussed	Line: Bussed	36.00	14.50	11.50
3	1	5	208Y/120	3 Gang	125	OH/UG	Lever	WML32125RJ	Bussed	Line: Bussed	46.00	14.50	11.50
3	1	5	208Y/120	4 Gang	125	OH/UG	Lever	WML42125RJ	Bussed	Line: Bussed	56.00	14.50	11.50
3	1	5	208Y/120	5 Gang	125	OH/UG	Lever	WML52125RJ	Bussed	Line: Bussed	66.00	14.50	11.50
3	1	5	208Y/120	6 Gang	125	OH/UG	Lever	WML62125RJ	Bussed	Line: Bussed	76.00	14.50	11.50
3	1	5	120/240	2 Gang	125	OH/UG	Lever	ML21125RJ	Bussed	Line: Bussed	36.00	14.50	11.50
3	1	5	120/240	3 Gang	125	OH/UG	Lever	ML31125RJ	Bussed	Line: Bussed	46.00	14.50	11.50
3	1	5	120/240	4 Gang	125	OH/UG	Lever	ML41125RJ	Bussed	Line: Bussed	56.00	14.50	11.50
3	1	5	120/240	5 Gang	125	OH/UG	Lever	ML51125RJ	Bussed	Line: Bussed	66.00	14.50	11.50
3	1	5	120/240	6 Gang	125	OH/UG	Lever	ML61125RJ	Bussed	Line: Bussed	76.00	14.50	11.50
3	1	5	120/240	2 Gang	125	OH/UG	Lever	WML12125RJ	Bussed	Line: Bussed	36.00	14.50	11.50
3	1	5	120/240	3 Gang	125	OH/UG	Lever	WML31125RJ	Bussed	Line: Bussed	46.00	14.50	11.50
3	1	5	120/240	4 Gang	125	OH/UG	Lever	WML41125RJ	Bussed	Line: Bussed	56.00	14.50	11.50
3	1	5	120/240	5 Gang	125	OH/UG	Lever	WML51125RJ	Bussed	Line: Bussed	66.00	14.50	11.50
3	1	5	120/240	6 Gang	125	OH/UG	Lever	WML61125RJ	Bussed	Line: Bussed	76.00	14.50	11.50
PAK Metering													
3	1	5	120/240	Residential	200	OH/UG	Lever	WPL4212RJ	(2) - 4.0"	3/8" studs	36.75	33.50	9.00
3	1	5	120/240	Residential	200	OH/UG	Lever	WPL4312RJ	(2) - 4.0"	3/8" studs	49.75	33.50	9.00
3	1	5	120/240	Residential	200	OH/UG	Lever	WPL4412RJ	(2) - 4.0"	3/8" studs	62.75	33.50	9.00
3	1	5	120/240	Residential	200	OH/UG	Lever	WPL6412RJ	(2) - 4.0"	3/8" studs	62.75	33.50	9.00
3	1	5	120/240	Residential	200	OH/UG	Lever	WPL6512RJ	(2) - 4.0"	3/8" studs	49.75	53.38	9.00
3	1	5	120/240	Residential	200	OH/UG	Lever	WPL6612RJ	(2) - 4.0"	3/8" studs	49.75	53.38	9.00
3	1	5	120/240	Residential	200	OH/UG	Lever	WPL8612RJ	(2) - 4.0"	3/8" studs	49.75	57.63	9.00
3	1	5	120/240	Residential	200	OH/UG	Lever	WPL10612RJ	(2) - 4.0"	3/8" studs	49.75	57.63	9.00



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

MURRY METERING DEVICES LIST

Meter Mains - Residential												
Wire	Phase	Terminal	Volt	Amps	Type	Type	Catalog #	Max Hub	Min/Max Cdr. Size	Height(in)	Width(in)	Depth(in)
3	1	5	120/240	320	OH	Lever	JC0404L1400RLM	3.0"	Line: One #6 - 350kcmil	19.70	17.10	5.00
3	3	5	120/240	320	OH/UG	Lever	JA0816B1400RLTM	4.0"	Line: One #4-600kCML	29	27	6



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

EATON/CH METER SOCKETS AND CT ENCLOSURES LIST

APPLICATION					METER SOCKET- EATON/CH		BY-PASS	Number of Terminals	Max Hub Size	Height	Width	Depth
WIRES	PHASE	MAX VOLTS	SERVICE TYPE	CONTINUOUS AMPS	INSTALLATION TYPE	CATALOG NUMBER						
INDIVIDUAL METER SOCKETS												
3	1 (5-Terminal)	120/240		200	SELF CONTAINED OH/UG	UTTE5213T*CH	Lever	5	4"	19"	13"	4 15/16"
4	3 (7-terminal)	120/240		200	SELF CONTAINED OH/UG	UTTE7213*CH	Lever	7	4"	19"	13"	4 15/16"
3	1 (5-Terminal)	120/240		320	SELF CONTAINED OH/UG	1009722-CH	Lever	5	4"	34 5/8"	15"	5 11/16"
4	3 (7-terminal)	120/240		320	SELF CONTAINED OH/UG	1009771CH	Lever	7	4"	36 5/8"	15"	5 11/16"
INDIVIDUAL - INSTRUMENT RATED METER SOCKETS -- Illinois Only												
3 OR 4	1 & 3 (8-Terminal)	120/240		20	CT RATED OH/UG	ULTS8IC227CH (ILLINOIS ONLY)	Lever	8	2-1/2"	22"	12"	4 15/16"
4	3 (13-terminal)	120/240		20	CT RATED OH OR UG	ULTS131C228CH (ILLINOIS ONLY)	Lever	13	2-1/2"	22"	12"	4 15/16"
HORIZONTAL GANG												
3	3 (5-terminal)	120/240	2-GANG HORIZONTAL	200	SELF CONTAINED OH/UG	UT2H52353TCH	Lever	5	5"	23 9/16"	32 25/32"	6"
3	3 (5-terminal)	120/240	3-GANG HORIZONTAL	200	SELF CONTAINED OH/UG	UT3H52353TCH	Lever	5	5"	23 9/16"	43 29/32"	6"
3	3 (5-terminal)	120/240	4-GANG HORIZONTAL	200	SELF CONTAINED OH/UG	UT4H52353TCH	Lever	5	5"	23 9/16"	61 1/32"	6"
3	3 (5-terminal)	120/240	5-GANG HORIZONTAL	200	SELF CONTAINED OH/UG	UT5H52353TCH	Lever	5	5"	23 9/16"	72 5/32"	6"
3	3 (5-terminal)	120/240	6-GANG HORIZONTAL	200	SELF CONTAINED OH/UG	UT6H52353TCH	Lever	5	5"	23 9/16"	83 9/32"	6"
4	3 (7-terminal)	120/240	2-GANG HORIZONTAL	200	SELF CONTAINED OH/UG	UT2H72353TCH	Lever	7	5"	23 9/16"	32 25/32"	6"
4	3 (7-terminal)	120/240	3-GANG HORIZONTAL	200	SELF CONTAINED OH/UG	UT3H72393TCH	Lever	7	5"	23 9/16"	43 29/32"	6"
4	3 (7-terminal)	120/240	4-GANG HORIZONTAL	200	SELF CONTAINED OH/UG	UT4H72393TTCH	Lever	7	5"	23 9/16"	61 1/32"	6"
4	3 (7-terminal)	120/240	5-GANG HORIZONTAL	200	SELF CONTAINED OH/UG	UT5H72393TTCH	Lever	7	5"	23 9/16"	72 5/32"	6"
4	3 (7-terminal)	120/240	6-GANG HORIZONTAL	200	SELF CONTAINED OH/UG	UT6H72393TTCH	Lever	7	5"	23 9/16"	83 9/32"	6"

*Denotes Overhead Hub Style



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

EATON/CH METER SOCKETS AND CT ENCLOSURES LIST

Group Metering -- Meter Packs and Meter Stacks

WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	MAX AMPS	CATALOG NUMBER	# OF Terminals
3	1	1200	120/240	1 Gang	225	35MM120R12"	5
3	1	1200	120/240	2 Gang	225	35MM220R12"	5
3	1	1200	120/240	3 Gang	225	35MM320R12"	5
3	1	1200	120/240	4 Gang	225	35MM420R12"	5
3	1	1200	120/240	5 Gang	225	35MM420R12"	5
3	1	1200	120/240	4 Gang	400	35MM140R1240"	5
4	3	1200	120/208	1 Gang	225	37MM120R12"	7
4	3	1200	120/208	2 Gang	225	37MM220R12"	7
4	3	1200	120/208	3 Gang	225	37MM320R12"	7
4	3	1200	120/208	4 Gang	225	37MM420R12"	7
4	3	1200	120/208	1 Gang W/ Provisions for 2 200A Main	400	37MM140R12"	7
4	3	1200	120/208	1 Gang	400	37MM140R1240"	7

*Add C to suffix for copper meter stacks if required

Temporary Power Pole

3	1	600	120/240	Temporary Power Pole 100 MB	100		CHR7N7NSU100M
---	---	-----	---------	-----------------------------	-----	--	---------------

400-800A CT Sections (TOP) with Disconnects (Bottom), Wall Mounted Line Entry at Top, Load Exit at Bottom

4	3	201-400	120/240 OR 120/208	400A CT METERING BAR TYPE BUSSED CT WITH FUSED CLASS T PULLOUT DISCONNECT SWITCH LUGS FOR 500MCM OR 2-4/0		CTAP425NCM8CH	N/A
4	3	601-800A	120/240 OR 120/208	800A CT METERING BAR TYPE BUSSED CT WITH FUSED CLASS T DISCONNECT SWITCH WITH 3-500MCM LUGS		CTAT427NCM8CH	N/A
4	3	401-600	120/240 OR 120/208	600A CT METERING BAR TYPE BUSSED CT WITH FUSED CLASS T DISCONNECT SWITCH WITH 2-500MCM LUGS		CTAT426NCM8CH	N/A
4	3	201-400	120/240 OR 120/208	400A CT METERING BAR TYPE BUSSED CT WITH FUSED CLASS T PULLOUT DISCONNECT SWITCH WITH 600MCM LUGS		CTAT425NCM8CH	N/A
4	3	201-400	120/240 OR 120/208	400A CT METERING BAR TYPE BUSSED CT WITH FUSED 2-200A CLASS T PULLOUTS DISCONNECT SWITCH		CTAP4244NCM8CH	N/A

Cold Sequence Meter Tap Enclosure



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

EATON/CH METER SOCKETS AND CT ENCLOSURES LIST

WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	MAX AMPS	CATALOG NUMBER	Height	Width	Depth	Notes	# OF Terminals
3	1	600	277/480	2 Gang	2-200	ETNPRL3COLDSEQ					5
Meter Combo Unit with Branch Circuit Breakers											
3	1	200	120/240	2P, 200A Main Breaker	200	CMBXB200BTS	39 13/16"	14 3/16"	4 15/16"	Copper Bus Interior	5
3	1	200A	120/240	2P, 200A Main Breaker	200A	CMBX1212B200BTS	39 13/16"	14 3/16"	4 15/16"	Copper Bus Interior	5
3	1	200A	120/240	2P, 200A Main Breaker	200A	CMBX1212P200BTS	39 13/16"	14 3/16"	4 15/16"	Copper Bus Interior	5
3	1	200A	120/240	2P, 200A Main Breaker	200A	CMBX3242B200BTS	41 13/16"	14 3/16"	4 15/16"	Copper Bus Interior	5
3	1	200A	120/240	2P, 200A Main Breaker	200A	CMBXP200BTS	39 13/16"	14 3/16"	4 15/16"	Copper Bus Interior	5
3	1	150A	120/240	2P, 150A Main Breaker	150A	MBX2040B150BTS	39 13/16"	14 3/16"	4 15/16"	Aluminum Bus	5
3	1	200A	120/240	2P, 200A Main Breaker	200A	MBX2040B200BTS	39 13/16"	14 3/16"	4 15/16"	Aluminum Bus	5
3	1	200A	120/240	2P, 200A Main Breaker	200A	MBX2040PV200BTS	39 13/16"	14 3/16"	4 15/16"	Solar Rated, Aluminum	5
3	1	150A	120/240	2P, 150A Main Breaker	150A	MBX816B150BTS	39 13/16"	14 3/16"	4 15/16"	Aluminum Bus	5
3	1	200A	120/240	2P, 200A Main Breaker	200A	MBX816B200BTS	39 13/16"	14 3/16"	4 15/16"	Aluminum Bus	5



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

SQUARE D METER SOCKETS LIST

Wires	Phase	Volts	Max Amps	Installation Type	Catalog #	Hub (separate)	Lug Wire Range	Bypass Type
Individual Meter Sockets								
3	1	120/240	200A	OH	UTH4203T	Series A-L	L(1)6-350 G14-2	Lever
3	1	120/240	200A	OH/UG	UTH4213T	Series A-L	L(1)6-350 G14-2	Lever
3	1	120/240	200A	OH	UTH5203T	Series A-L	L(1)6-350 G14-2	Lever
3	1	120/240	200A	OH/UG	UTH5213T	Series A-L	L(1)6-350 G14-2	Lever
4	3	120/240	200A	OH/UG	UTH7213T	Series A-L	L(1)6-350 G14-2	Lever
3	1	120/240	320A	OH/UG	1009722-SQD			Lever
4	3	120/240	320A	OH	UTH7300T	Series A-L	Studs Only	Lever
Meter/Main Combination								
3	1	120/240	200A	OH/UG	RCM200SL	Series A	(1) 6 - 350	Lever
3	1	120/240	200A	OH/UG	RC2M200SL	Series A	(1) 6 - 350	Lever
3	1	120/240	400A	UG	QU12L400SL	Series A-L	(2) Stubs G(1)4-250	Lever
3	1	120/240	150A	OH/UG	QC816F150SL	Series A	(1) 6 - 350	Lever
3	1	120/240	200A	OH/UG	QC816F200SL	Series A	(1) 6-350	Lever
3	1	120/240	400A	OH/UG	QUM400CL	Series A	Lugs ordered separately	Lever
3	1	120/240	400A	UG	QU816D400FL	Series A	Lugs ordered separately	Lever
3	1	120/240	400A	UG	QU816D400SL	Series A-L	(2) Stubs G(1)4-250	Lever
3	1	120/240	400A	UG	QU816D400CL	Series A-L	(2) Stubs G(1)4-250	Lever
3	1	120/240	400A	UG	QU12L400CL	Series A	Lugs ordered separately	Lever
3	1	120/240	400A	UG	QU12L400FL	Series A	Lugs ordered separately	Lever
3	1	120/240	150A	OH/UG	RC816F150SL	Series A	(1) 6 - 350	Lever
3	1	120/240	200A	OH/UG	RC816F200SL	Series A	(1) 6 - 350	Lever
3	1	120/240	150A	OH/UG	RC3040M150SL	Series A or B300	Lugs ordered separately	Lever
3	1	120/240	200A	OH/UG	RC3040M200SL	Series A or B300	Lugs ordered separately	Lever
3	1	120/240	400A	UG	RU3040D400FL	Series A	Lugs ordered separately	Lever
3	1	120/240	400A	UG	RU3040D400CL	Series A-L	(2) Stubs G(1)4-250	Lever
MP Meter-Pak Meter Centers						Amps Per Pos.		
3	1	120/240	350	OH/UG	MPL32225	225A	(1)1/0-600 or (2)1/0-250	Lever
3	1	120/240	500	OH/UG	MPL53225	225A	(1)1/0-600 or (2)1/0-250	Lever
3	1	120/240	600	OH/UG	MPL64225	225A	(1)1/0-600 or (2)1/0-250	Lever
EZ Meter-Pak Meter Centers - Single Phase (Note: order single phase meter sockets in addition to the meter center)								
3	1	120/240	400A	OH/UG	EZM1400CB	Circuit Breaker	L(1)600 or (2)1-250	
3	1	120/240	600A	OH/UG	EZM1600CB	Circuit Breaker	L(3)3/0-500	
3	1	120/240	800A	OH/UG	EZM1800CB	Circuit Breaker	L(3)3/0-500	
3	1	120/240	1000A	OH/UG	EZM11000CB	Circuit Breaker	L(3)3/0-500	
3	1	120/240	1200A	OH/UG	EZM11200CB	Circuit Breaker	L(4)1/0-750	
3	1	120/240	1600A	OH/UG	EZM11600CB	Circuit Breaker	L(6)1/0-750	
3	1	120/240	2000A	OH/UG	EZM12000CB	Circuit Breaker	L(6)1/0-750 or (12)1/0-250	
3	1	120/240	400A	OH/UG	EZM1400FS	Fusible	L(1)1-600 or (2)1-250	
3	1	120/240	600A	OH/UG	EZM1600FS	Fusible	L(3)3/0-500	
3	1	120/240	800A	OH/UG	EZM1800FS	Fusible	L(3)3/0-500	
3	1	120/240	1200A	OH/UG	EZM11200FS	Fusible	L(4)1/0-750	
3	1	120/240	225A	OH/UG	EZM1225TB	Main Lugs	L(1)4-300	
3	1	120/240	400A	OH/UG	EZM1400TB	Main Lugs	L(2)3/0-500	
3	1	120/240	600A	OH/UG	EZM1600TB	Main Lugs	L(2)1/0-750 or (4)1/0-300	
3	1	120/240	800A	OH/UG	EZM1800TB	Main Lugs	L(4)3/0-500	
3	1	120/240	800A	OH/UG	EZM1800TBCU	Main Lugs	L(4)3/0-500	
3	1	120/240	1600A	OH/UG	EZM11600TB	Main Lugs	L(6)3/0-600	
3	1	120/241	2000A	OH/UG	EZM12000TB	Main Lugs	Lugs Ordered Separately	
3	1	120/240	400A	UG	EZM1400CBU	Circuit Breaker	Factory Installed Lug Landings	
3	1	120/240	600A	UG	EZM1600CBU	Circuit Breaker	Factory Installed Lug Landings	
3	1	120/240	800A	UG	EZM1800CBU	Circuit Breaker	Factory Installed Lug Landings	



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

SQUARE D METER SOCKETS LIST

Wires	Phase	Volts	Max Amps	Installation Type	Catalog #	Hub (separate)	Lug Wire Range	Bypass Type
3	1	120/240	1000A	UG	EZM11000CBU	Circuit Breaker	Factory Installed Lug Landings	
3	1	120/240	1200A	UG	EZM11200CBU	Circuit Breaker	Factory Installed Lug Landings	
3	1	120/240	1600A	UG	EZM11600CBU	Circuit Breaker	Factory Installed Lug Landings	
3	1	120/240	2000A	UG	EZM12000CBU	Circuit Breaker	Factory Installed Lug Landings	
3	1	120/240	400A	UG	EZM1400FSU	Fusible	Factory Installed Lug Landings	
3	1	120/240	600A	UG	EZM1600FSU	Fusible	Factory Installed Lug Landings	
3	1	120/240	800A	UG	EZM1800FSU	Fusible	Factory Installed Lug Landings	
3	1	120/240	1200A	UG	EZM11200FSU	Fusible	Factory Installed Lug Landings	
3	1	120/240	400A	UG	EZM1400TBU	Main Lugs	Factory Installed Lug Landings	
3	1	120/240	800A	UG	EZM1800TBU	Main Lugs	Factory Installed Lug Landings	
3	1	120/240	1200A	UG	EZM11200TBU	Main Lugs	Factory Installed Lug Landings	
EZ Meter-Pak Meter Single Phase Sockets						Branch Device	Breaker	
3	1	120/240	1200A	Branch Units	EZML111225	1 Socket	225A	Lever
3	1	120/240	1200A	Branch Units	EZML111225CU	1 Socket	225A	Lever
3	1	120/240	1200A	Branch Units	EZML111225D	1 Socket	225A	Lever
3	1	120/240	1200A	Branch Units	EZML112225	2 Sockets	225A	Lever
3	1	120/240	1200A	Branch Units	EZML112225CU	2 Sockets	225A	Lever
3	1	120/240	1200A	Branch Units	EZML112225D	2 Sockets	225A	Lever
3	1	120/240	1200A	Branch Units	EZML113225	3 Sockets	225A	Lever
3	1	120/240	1200A	Branch Units	EZML113225CU	3 Sockets	225A	Lever
3	1	120/240	1200A	Branch Units	EZML113225D	3 Sockets	225A	Lever
3	1	120/240	1200A	Branch Units	EZML111400	1 Socket	400A	Lever
3	1	120/240	1200A	Branch Units	EZML112400	2 Sockets	400A	Lever
EZ Meter-Pak Meter Centers - Three Phase (Note:order three-phase meter sockets in addition to the meter center)						Main Device		
4	3	208Y/120 or 240/120	400A	OH/UG	EZM3400CB	Circuit Breaker	L(1)1-600 or (2)1-250	
4	3	208Y/120 or 240/120	600A	OH/UG	EZM3600CB	Circuit Breaker	L(3)3/0-500	
4	3	208Y/120 or 240/120	800A	OH/UG	EZM3800CB	Circuit Breaker	L(3)3/0-500	
4	3	208Y/120 or 240/120	1000A	OH/UG	EZM31000CB	Circuit Breaker	L(3)3/0-500	
4	3	208Y/120 or 240/120	1200A	OH/UG	EZM31200CB	Circuit Breaker	L(4)1/0-750	
4	3	208Y/120 or 240/120	1600A	OH/UG	EZM31600CB	Circuit Breaker	L(6)1/0-750	
4	3	208Y/120 or 240/120	2000A	OH/UG	EZM32000CB	Circuit Breaker	L(6)1/0-750 or (12)1/0-250	
4	3	208Y/120 or 240/120	400A	OH/UG	EZM3400FS	Fusible	L(1)1-600 or (2)1-250	
4	3	208Y/120 or 240/120	600A	OH/UG	EZM3600FS	Fusible	L(3)3/0-500	
4	3	208Y/120 or 240/120	800A	OH/UG	EZM3800FS	Fusible	L(3)3/0-500	
4	3	208Y/120 or 240/120	225A	OH/UG	EZM3225TB	Main Lugs	L(1)4-300	
4	3	208Y/120 or 240/120	400A	OH/UG	EZM3400TB	Main Lugs	L(2)3/0-500	
4	3	208Y/120 or 240/120	600A	OH/UG	EZM3600TB	Main Lugs	L(2)1/0-750 or (4)1/0-300	
4	3	208Y/120 or 240/120	800A	OH/UG	EZM3800TB	Main Lugs	L(4)3/0-500	
4	3	208Y/120 or 240/120	800A	OH/UG	EZM3800TBCU	Main Lugs	L(4)3/0-500	
4	3	208Y/120 or 240/120	1600A	OH/UG	EZM31600TB	Main Lugs	L(6)3/0-600	
4	3	208Y/120 or 240/120	2000A	OH/UG	EZM32000TB	Main Lugs	Lugs Ordered Separately	
EZ Meter-Pak Meter Sockets - Three Phase						Branch Device	Maximum Circuit Breaker	
4	3	208Y/120	1200A	Branch Units	EZML311225	1 Sockets	225A	Lever
4	3	208Y/120	1200A	Branch Units	EZML311225CU	1 Sockets	225A	Lever
4	3	208Y/120	1200A	Branch Units	EZML311225D	1 Sockets	225A	Lever
4	3	208Y/120	1200A	Branch Units	EZML312225	2 Sockets	225A	Lever
4	3	208Y/120	1200A	Branch Units	EZML312225CU	2 Sockets	225A	Lever
4	3	208Y/120	1200A	Branch Units	EZML312225D	2 Sockets	225A	Lever
4	3	208Y/120	1200A	Branch Units	EZML313225	3 Sockets	225A	Lever
4	3	208Y/120	1200A	Branch Units	EZML313225CU	3 Sockets	225A	Lever
4	3	208Y/120	1200A	Branch Units	EZML313225D	3 Sockets	225A	Lever
4	3	208Y/120	1200A	Branch Units	EZML314225	4 Sockets	225A	Lever
4	3	208Y/120	1200A	Branch Units	EZML314225CU	4 Sockets	225A	Lever



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

SQUARE D METER SOCKETS LIST

Wires	Phase	Volts	Max Amps	Installation Type	Catalog #	Hub (separate)	Lug Wire Range	Bypass Type
4	3		1200A	Branch Units	EZML314225D	4 Sockets	225A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML331225	1 Socket	225A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML331225CU	1 Socket	225A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZM331225D	1 Socket	225A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML332225	2 Sockets	225A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML332225CU	2 Sockets	225A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML332225D	2 Sockets	225A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML333225	3 Sockets	225A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML333225CU	3 Sockets	225A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML333225D	3 Sockets	225A	Lever
			1200A	Branch Units	EZML334225	4 Sockets	225A	Lever
			1200A	Branch Units	EZML334225CU	4 Sockets	225A	Lever
			1200A	Branch Units	EZML334225D	4 Sockets	225A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML311400	1 Socket	400A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML312400	2 Sockets	400A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML331400	1 Socket	400A	Lever
4	3	208Y/120 or 240/120	1200A	Branch Units	EZML332400	2 Sockets	400A	Lever

SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

MIDWEST ELECTRIC SOCKET & BREAKER COMBINATIONS LIST

Wires	Phase	Terminals	Volts	Service Type	Amps	Installation	Bypass	Catalog#
Temporary Power - Surface Mount - Residential								
3	1	4 or 5*	120/240	Temp with 3 circuit spaces	100	UG (1.5")	Hom	R011C010U
3	1	4 or 5*	120/240	Temp with 3 circuit spaces	100	OH	Hom	R011C010
3	1	4 or 5*	120/240	Temp with 6 circuit spaces	100	OH	Hom	R101CB2010
		*5th jaw kit	120/208					MS5
Combination Sockets - Surface Mount								
3	1	5	120/240	Main with 4 circuit spaces	200	OH/UG (3")	Lever	R281CB1034
3	1	5	120/240	Main with 4 circuit spaces	200	OH	Lever	R281C1034
Metered Combination Pedestal Units								
3	1	5	120/240	Main with 4 circuit spaces	200	UG	Lever	R481C1P6H034
3	1	5	120/240	Main with 4 circuit spaces	200	UG	Lever	R281C1P6H034
3	1	5	120/240	Main with 4 circuit spaces	200	UG	Lever	R281E1P6H034



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

GE METER COMBO SOCKETS LIST

WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	MAX AMPS	CATALOG NUMBER	TERMINALS	SIZE	NUMBER
3	1	1200	120/240	1 Gang	225	TMPR12122R	5	3"	96-1988
3	1	1200	120/240	2 Gang	225	TMPR12222R	5	3"	96-1988
3	1	1200	120/240	3 Gang	225	TMPR12322R	5	3"	96-1988
3	1	1200	120/240	4 Gang	225	TMPR12422R	5	3"	96-1988
3	1	1200	120/240	1 Gang	400	TMPR12140RB	5	3"	96-4754
3	1	1200	120/240	2 Gang	400	TMPR12240RB	5	3"	96-5814
4	3	1200	120/208	1 Gang	225	TMPR312122R	5	3"	96-1988
4	3	1200	120/208	2 Gang	225	TMPR312222R	5	3"	96-1988
4	3	1200	120/208	3 Gang	225	TMPR312322R	5	3"	96-1988
4	3	1200	120/208	4 Gang	225	TMPR312422R	5	3"	96-1988
4	3	1200	120/208	1 Gang W/ Provisions for 2-200A Main Breakers	400	TMPR312140TR	5	3"	96-1988
4	3	1200	120/208	1 Gang	400	TMPR312140RB	5	3"	96-4754
4	3	1200	120/208	2 Gang	400	TMPR312240RB	5	3"	96-5814
4	3	up to 5000	480/277	3 Gang in Switchboard	200	Spectra Switchboard using Milbank P/N Z911500-AC	7	4"	10094423



SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

COOPER B-LINE METER SOCKETS LIST

APPLICATION						AMEREN METER SOCKETS APPROVAL LIST			NUMBER OF TERMINALS	MAX HUB SIZE
WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	MAX AMPS	INSTALLATION TYPE	BY-PASS	CATALOG NUMBER		
METER/MAIN COMBO - 320AMP										
4	3	320A	120/240	-	320A	SELF-CONTAINED OH/UG	LEVER	EL32T76GRST	7	4"
3	1	320A	120/240	-	320A	SELF-CONTAINED UG W/2-200A CB	LEVER	ELCB32C25A4GR1F	5	NONE
METER/MAIN COMBO - 200AMP AND BELOW										
4	3	200A/POSITION	120/240	-	0-200A	SELF-CONTAINED OH/UG	LEVER	EL20L73GRST	7	4"
3	1	200A/POSITION	120/240	-	0-200A	SELF-CONTAINED OH/UG	LEVER	EL20L53GRST	5	4"
4	3	200A/POSITION	240V MAX.	2 GANG	0-200A	SELF-CONTAINED OH/UG	LEVER	HEL20732CGR1N	7	2 1/2"
3	1	200A/POSITION	120/240	2 GANG	0-200A	SELF-CONTAINED OH/UG	LEVER	HEL20432CGR1N	5	2 1/2"
3	1	200A/POSITION	120/240	3 GANG	0-200A	SELF-CONTAINED OH/UG	LEVER	HEL20433CGR1N	5	2 1/2"
3	1	200A/POSITION	120/240	4 GANG	0-200A	SELF-CONTAINED OH/UG	LEVER	HEL20434CGR1N	5	2 1/2"
3	1	200A/POSITION	120/240	2 GANG	0-200A	SELF-CONTAINED OH/UG w/ CB PROVISION	LEVER	VELMP20432LGRST5K9	5	2 1/2"
3	1	200A/POSITION	120/240	3 GANG	0-200A	SELF-CONTAINED OH/UG (with 2 1/2" k.O Left)	LEVER	VELMP20433CGRST5K9	5	2 1/2"
3	1	200A/POSITION	120/240	4 GANG	0-200A	SELF-CONTAINED OH/UG w/ CB PROVISION	LEVER	VELMP20434CGRST5K9	5	2 1/2"
3	1	200A/POSITION	120/240	5 GANG	0-200A	SELF-CONTAINED OH/UG w/ CB PROVISION	LEVER	VELMP20435CGRST5K9	5	2 1/2"
4	3	200A/POSITION	240V MAX.	3 GANG	0-200A	SELF-CONTAINED OH/UG	LEVER	HEL20733CGR1N	7	2 1/2"
4	3	200A/POSITION	240V MAX.	4 GANG	0-200A	SELF-CONTAINED OH/UG	LEVER	HEL20734CGR1N	7	2 1/2"

SECTION 1100. AMEREN APPROVED METER MOUNTING DEVICES LIST

INDIVIDUAL 480V FUSED DISCONNECT OR BREAKER

WIRES	PHASE	SERVICE AMPS	VOLTS	MANUFACTURER		CATALOG NUMBER
4	3	200	277/480	Boltswitch	Fused Disconnect	OH
2 OR 3	1 OR 3	200	480	Boltswitch	Fused Disconnect	ENPT364-2P